



CWST

Heat-shrinkable wraparound repair sleeve

- CWST repair sleeves are based on the RayFort technology of heat shrinkable composite materials. The CWST wraparound sleeves are suitable for repair of all types of unpressurised cable: aerial, buried or ducted, non filled or jelly filled with polyethylene or metal jackets.
- An integrated moisture barrier completely reconstitutes the cable sheath construction.
- The hotmelt adhesive coated on the sleeve ensures a permanent, reliable, watertight seal.
- The excellent split resistance of the composite structure offers superior resistance to mechanical abuse during and after the installation.
- The installation indicators: heat sensitive paint, adhesive flow and the white line facilitate correct installations.
- Unlimited shelf life.
- Extended size range can accommodate cables with diameters ranging from 8 to 200 mm.



This cable jacket, damaged by an excavator, is quickly repaired.



The CWST sleeve is simply wrapped around the damaged cable area and shrunk with a standard jointer's torch.

Sizing/ordering information

Dimension in mm

Description	Max. cable dia.	Min. cable dia.	Lengths supplied
CWST 43/8	43	8	1500, 1000, 750, 500, 250
CWST 55/12	55	12	1500, 1000, 750, 500, 250
CWST 75/15	75	15	1500, 1000, 750, 500, 250
CWST 100/25	100	25	1500, 1000, 750, 500, 250
CWST 137/34	137	34	1500, 1000, 750, 500, 250
CWST 125/30	125	30	1500, 1000, 750, 500, 250
CWST 164/42	164	42	1500, 1000, 750, 500, 250
CWST 200/50	200	50	1500, 1000, 750, 500, 250

Tyco Electronics and TE logo are trademarks.

The information given herein, including drawings, illustrations and schematics which are intended for illustration purposes only, is believed to be reliable. However, Tyco Electronics makes no warranties as to its accuracy or completeness and disclaims any liability in connection with its use. Tyco Electronics' obligations shall only be as set forth in Tyco Electronics' Standard Terms and Conditions of Sale for this product and in no case will Tyco Electronics be liable for any incidental, indirect or consequential damages arising out of the sale, resale, use or misuse of the product. Users of Tyco Electronics products should make their own evaluation to determine the suitability of each such product for the specific application.

Tyco Electronics Raychem bvba

Diestsesteenweg 692

3010 Kessel-Lo, Belgium

Tel 32-16 351 011 (USA)1-919-557-8900

Fax 32-16 351 697 (USA)1-919-557-8498

www.tycoelectronics.com

www.telecomosp.com

TC 228/DS/6 04/07